# PRAIRIE LABS, INC.



Model CIC 9000

- Standard One Year Warranty
- One Year Loss and Damage included\*
- Size 10A battery
- Replaceable swing-out battery door
- Gold plated battery contacts
- Switched Volume Control
- Wax removal brush
- Helpful hint booklet
- One free premium zinc air battery
- Pouch



## **Charged options:**

User adjustable micro-VC (no off/on switch)

Push button digital VC (class D only)

### **Analog Amplifier choices:**

#### Class A Amplifier

- -- Up to 30 dB H.F.A. full gain
- -- Up to 110dB SSPL
- -- 0.5 MA battery drain
- -- Up to 140hours of battery life with size 10A zinc air battery

#### Push Pull Amplifier

- -- Up to 50 dB H.F.A. full on gain
- -- Up to 120 dB SSPL
- -- Battery drain of 1.5 MA
- -- Battery life: up to 80 hours with size 10A zinc air battery

#### Class D Amplifier

- -- Up to 40 dB H.F.A. full on gain
- -- Up to 120 dB SSPL
- -- Battery drain of 0.4 MA
- -- Battery life: up to 170 hours with size 10A zinc air battery

#### Low Drain Amplifier (Class A Only)

- -- Up to 30 dB H.F.A. full on gain
- -- Up to 105 dB SSPL
- -- Battery drain of 0.3 MA
- -- Battery life: up to 200 hours with size 10A zinc air battery

### AGC Amplifier

- -- Up to 30 dB H.F.A. full on gain
- -- Up to 110 dB SSPL
- -- Battery drain of 0.4 MA
- -- Battery life: up to 170 hours with size 10A zinc air battery

#### AGC/Class D Amplifier

- -- Up to 40 dB H.F.A. full on gain
- -- Up to 120 dB SSPL
- -- Battery drain of 0.4 MA
- -- Battery life: up to 170 hours with size 10A zinc air battery

Toggle Switch may be substituted for a pot at no extra charge. Battery life may vary depending on ambient noise, temperature etc.

\* A processing fee will apply: please call us at (800)322-8238, or visit our website at <a href="http://www.prairielabs.com">http://www.prairielabs.com</a> for more information.